

Xantrex™ Solar Charge Controller XW-MPPT60-150



The Xantrex™ XW Solar Charge Controller is a photovoltaic (PV) charge controller that tracks the electrical maximum power point of a PV array to deliver the maximum available current for charging batteries. When charging, the XW Solar Charge Controller regulates battery voltage and output current based on the amount of energy available from the PV array and state-of-charge of the battery.

The XW Solar Charge Controller can be used with 12, 24, 36, 48, and 60-volt DC battery systems and is able to charge a lower nominal-voltage battery from a higher nominal-voltage array. For example, the XW Solar Charge Controller can charge a 12-volt battery from a 36-volt array. This provides flexibility for installers to use longer wiring runs without compromising efficiency. The XW Solar Charge Controller can be installed in single or multi-unit configurations with a Xantrex XW Hybrid Inverter/Charger or can be used in other solar energy systems where a solar charge controller is needed.

The XW Solar Charge Controller incorporates a dynamic Maximum Power Point Tracking (MPPT) algorithm designed to maximize energy harvest from the PV array. The MPPT constantly adjusts the operating points of the array to ensure it stays on the maximum power point. It does not stop energy harvest to sweep the array like some other competing products. This feature is beneficial in all sunlight conditions, especially in areas with fast moving cloud cover and quickly changing solar conditions.

Product features

- ▶ Maximum Power Point Tracking (MPPT) delivers maximum available power from PV array to battery bank
- ▶ Integrated PV ground-fault protection
- ▶ Ultra-reliable, convection-cooled design does not require a cooling fan – large, aluminum, die-cast heat-sink allows full output current up to 45°C without thermal derating
- ▶ Selectable two or three stage charging algorithms with manual equalization to maximize system performance and improve battery life
- ▶ Configurable auxiliary output
- ▶ Two-line, 16-character liquid crystal display (LCD) and four buttons for configuration and system monitoring
- ▶ Input over-voltage and under-voltage protection, output over-current protection, and backfeed (reverse current) protection (warning and fault messages appear on LCD when unit shuts down as a protective measure)
- ▶ Over-temperature protection and power derating when output power and ambient temperature are high
- ▶ Battery Temperature Sensor (BTS) included – automatically provides temperature-compensated battery charging
- ▶ Xanbus™-enabled network communications protocol (developed by Xantrex)
- ▶ Communicates settings and activity to other Xanbus™-enabled devices, such as the XW Hybrid Inverter/Charger, the XW System Control Panel (XW SCP), XW Automatic Generator Start (XW AGS), and other XW Solar Charge Controllers
- ▶ Five-year warranty (10 year warranty optional)

Xantrex™ Technology Inc.

Headquarters

8999 Nelson Way
Burnaby, British Columbia
Canada V5A 4B5
+1 800 670 0707 Toll Free
+1 604 420 1591 Fax
pvsales@xantrex.com

Europe

Xantrex Technology GmbH
Steinheimer Str. 117
63500 Seligenstadt, Germany
+49 (0) 6182 81 6000 Tel
+49 (0) 6182 81 6001 Fax

Xantrex Technology S.L.

Bac de Roda, 52 edificio A
08019 Barcelona, Spain
+34 93 433 8350 Tel
+34 93 433 8351 Fax
europesales@xantrex.com



Our evolution to Schneider Electric, the global specialist in energy management, re-affirms our commitment to provide you with innovative solutions, best-in-class customer service, and exceptional quality in everything we do. We are proud to be your partner, and we are dedicated to helping you make the most of your energy.

www.xantrex.com

Xantrex™ XW Solar Charge Controller

Electrical Specifications

| | |
|--|---|
| Nominal battery voltage | 12, 24, 36, 48, 60 Vdc |
| Maximum PV array voltage (operating) | 140 Vdc |
| Maximum PV array open circuit voltage | 150 Vdc |
| Array short-circuit current | 60 Adc maximum |
| Maximum and minimum wire size in conduit | #6 AWG to #14 AWG |
| Total power consumption while operating | 2.5 W (tare) |
| Charger regulation method | Three-stage (bulk, absorption, float) Two-stage (bulk, absorption) |

Mechanical Specifications

| | |
|---------------------------------|--|
| Dimensions (H × W × D) | 14 ½ × 5 ¾ × 5 ½" (368 × 146 × 138 mm) |
| Weight (controller only) | 10.75 lb (4.8 kg) |
| Weight (shipping) | 17.6 lb (8 kg) |
| Shipping dimensions (H × W × D) | 19 × 9 × 9 ¾" (483 × 229 × 350 mm) |
| Mounting | Vertical wall mount |
| Standard warranty | Five years (10 years optional) |
| Part number | 865-1030 |

Environmental Specifications

| | |
|--|---|
| Enclosure type | Indoor, ventilated, sheet metal chassis with 7/8" and 1" (22.22 mm and 27.76 mm) knockouts and aluminum heat-sink |
| Operating temperature range (full power) | -4 to 113 °F (-20 to +45 °C) |
| Storage temperature | -40 to 185 °F (-40 to +85 °C) |
| Altitude limit (operating) | Sea level to 15,000 feet (4572 m) @ 15 °C |

Regulatory Approvals

CSA certified to CSA 107.1, UL 1741 FCC Class B and Industry Canada, CE

Optional Accessories

| | |
|------------------------------|----------|
| XW System Control Panel | 865-1050 |
| XW Automatic Generator Start | 865-1060 |
| Network cables: | |
| 3 feet (0.9 m) | 809-0935 |
| 25 feet (7.6 m) | 809-0940 |
| 50 feet (15.2 m) | 809-0941 |
| 75 feet (22.9 m) | 809-0942 |

Specifications subject to change without notice.

For more information on the XW System please visit www.xantrex.com/xw