

MODEL			PV2000				
Nominal Power			2000W				
AC Input							
Phase & waveform	Single phase & Pure Sine Wave						
Voltage	120VAC						
Acceptable Voltage	95-126VAC						
Low Line Disconnect	85VAC±4%						
Low Line Re-connect	95VAC±4%						
High Line Disconnect	136VAC±4%						
High Line Re-connect	126VAC±4%						
Frequency	60Hz						
AC Output							
Phase & waveform	Single phase & Pure Sine Wave (bypass mode sync to input)						
Voltage	120VAC 10%rms (bypass mode sync to input)						
Frequency	60Hz±0.3Hz (bypass mode sync to input)						
Peak Power	3 times of rating power						
Short Circuit Protection	Yes, shutdown after 10ms						
Power Factor	0.9-1.0						
DC Input							
Battery Voltage	12VDC						
Minimum Start Voltage	10VDC						
Low Battery Alarm	10.5±0.3vdc						
Low DC input Shut-down	10±0.3vdc						
High DC input Alarm & Fault	16±0.3vdc						
High DC input Recovery	15.5±0.3vdc						
MAX Charger Current	70 AMP						
System parameter							
Battery Mode Efficiency	>85%						
Line Mode Efficiency	>96%						
power saver	Load ≤25W (Enabled on "P/S auto" setting of Remote control)						
Audible Alarm	Sounding when the heat sink's tem is over 100°C and shutdown after 30 seconds.						
Over Load Protection	110%<load≤="" font=""></load Load>150%, beeps 0.5s every 1s, and Fault after 20s.						
Protections	low battery、 over charging、 over temp、 over load						
Communications	RS-232/USB/SNMP(custom-made)						
Operating Environment	0-40°C,0-90%RH(non-condensing)						
Audible Noise	<60dB						
Net Weight(KG)			20kg				
Dimension L X W X H	470 X223 X185mm						

